

ErP Power Mode Information Sheet

Number: 16-002

Revision: 1



WorkCentre 3335

Device Type: Multifunction Device
ErP Equipment Type: Other Networked Equipment

POWER SUPPLY

Voltage (Volts) 230
Output Rating (Watts) 700

POWER MODE

	Power (Watts)	Default Period (Minutes)
Active	647.5	Not applicable
Ready/Standby	48.2	0
Sleep 1	2.2	1
Plugged In Off	0.0	Not applicable
Networked Standby - All	2.3	Not applicable
Networked Standby - USB	2.2	1
Networked Standby - Ethernet	2.3	1
Networked Standby - Wireless	2.3	1
Networked Standby - FAX	2.3	1

GUIDANCE – WIRELESS PORT

1. Press **Login**. Log in as **admin / 1111**
2. Press **Machine Status**
3. Scroll down to **Network Settings**. Touch **Network Settings**
4. Touch **Network Connectivity**
5. Touch the arrow on right to open the **Wired / Wireless** selection option window.
6. Select **Wired** to disable wireless.
7. Select **Wireless** to enable wireless. Select the desired wireless network and then enter the network password.

For more information about Xerox environmental programs in *North America*, refer to: www.xerox.com/Environment
For more information about Xerox environmental programs in *Europe*, refer to: www.xerox.com/environment_europe

Xerox Corporation provides Power Mode Information Sheets in response to the provisions of ErP Directive 2009/125/EC with regard to eco-design requirements for standby, off mode power consumption of applicable networked printers according to Commission Regulations (EC) No 1275/2008 of 17 December 2008 and (EU) No 801/2013 of 22 August 2013 [Form Rev-1g]