

Product Safety Data Sheet

SDS #: 16-00640

2017-05-31 Revision 3

Xerox Brenva HD Production Inkjet Press (Print Module)

Product Identifier Production Printer / BDC-1

Speed (PPM) 180 Mono / Color Colour

ELECTRICAL INPUT INFORMATION

 Voltage (Volts)
 120V/208V
 220-240V/380-415V

 Rated Current (Amperes):
 50A
 25A

 Frequency (Hertz)
 60
 50/60

 Phase Connection
 three
 three

POWER AND HEAT

	Power	Heat Output	Power	Heat Output
	(Watts)	(BTU/Hr)	(Watts)	(BTU/Hr)
Active ¹	13721	46818	12415	42362
Ready ¹	2200	7507	2000	6824

¹ Power states defined per ENERGY STAR Program requirements for Imaging Equipment: Version 1.2

Note: The electrical power information provided should not be used to define the electrical support required for this product. Consult your Xerox representative if you require detailed information.

OPERATING ENVIRONMENT

Relative Humidity % 35-55%

Ambient Temperature 68-77 °F / 20-25 °C

PRODUCT SIZE

 Depth
 58 in.
 147.32 cm

 Width
 190.5 in.
 483.9 cm

 Height
 80 in.
 203.2 cm

 Weight
 4365 lbs
 1980 kg

SPACE REQUIREMENTS

Refer to Installation Planning Guide

For additional information regarding different configurations please contact your local sales representative.

LIGHT SOURCE: Class 1 Laser product containing an embedded Class 3B Laser

ACOUSTICAL NOISE

Tested in accordance to ISO 7779 and declared per ISO 9296

Sound Power Level LwAd (B) LpAd (dBA)
Standby - 68.0
Run - continuous - 72.0

Xerox Corporation has developed this Product Safety Data sheet for informational purposes as a courtesy for Xerox customers. Any determination regarding the proper use of this information must be made by the user, including any use of the information for compliance with applicable laws, rules and regulations. Xerox believes the information herein to be accurate as of the date of issuance but makes no representations or warranties of any kind, either express or implied, as to the accuracy, completeness or fitness for use of the information. By issaunce of this Product Safety Data Sheet, Xerox does not assume any liability or responsibility for losses, claims, liabilities or damages which may result from reliance upon the information herein.